



## GPS 6600A

Portable Generators



### Rugged and powerful premium portable power

Designed for construction, rental and other demanding applications, these quiet, high-performance, portable generators deliver unmatched tool starting and voltage regulation in a rugged compact package. Excellent for powering single or multiple tools on an entire job site or as emergency or standby power. Built with heavy-duty frames and premium components to provide long, trouble-free operation even in abusive environments. Ideal for powering high starting amperage tools such as compressors, grinders, fusion welders as well as all your Wacker Neuson electric power tools.

- Best in class tool starting and voltage regulation due to a unique step-start generator technology with AVR (automatic voltage regulation) and separate excitation winding.
- Central GFCI (neutral bonded to ground) sensor system eliminates common GFI outlet failures while offering personal protection on all receptacles including 240 Volt.
- Unique auto-idle control with time delay system automatically reduces the engine to a low speed reducing fuel consumption, noise and wear.
- Full wrap-around frame with dual cross-member support, high impact polyethylene fuel tank and heavy duty shock-mounting combine to provide outstanding impact protection.
- Honda engine with low oil shutdown and electric start. Fully compliant with the latest EPA evaporative emissions regulations.



## Technical specifications

### Portable Premium Generators

#### Dimensions

L x W x H Overall	34.25 x 21 x 21.2 in
L x W x H Shipping	28 x 27 x 23.2 in
Weight Dry	213 lb
Shipping weight without Fuel	218 lb

#### Operating data

Operating weight with Fuel	243 lb
Circuit breaker AC - 1 Phase 2 Pole	27 A
Receptacles AC Outlet	(2) 125V, 20A Duplex
Receptacles AC Outlet	125/ 250V, 30A Twst Loc
Receptacles AC Outlet	125V, 30A Twist Lock

#### Electrical system

Electrical power Max. Output	6,600 W
Electrical power Continuous Power	6,000 W
Voltage AC - 1 Phase	120/ 240 V
Current AC - 1 Phase	50/ 25 A
Frequency	60 Hz
Power factor	1 cos $\Phi$ 1~
Generator model	AVR With Brushes
Power Rating Specification	SAE J1349

#### Engine / Motor

Engine / Motor	Honda
Engine / Motor manufacturer	GX390RT2
Cylinder	1
Displacement	23.7 in <sup>3</sup>
Operating performance	11.7 kW
RPM / speed Operating	3,600 rpm
Tank capacity Fuel	4.94 US qt



Tank capacity Oil	1.2 US gal
Fuel type	Gasoline
Fuel consumption	1 US gal/h
Runtime	4.8 h

**Please note**

that product availability can vary from country to country. It is possible that information / products may not be available in your country. More detailed information on engine power can be found in the operator's manual; the stated power may vary due to specific operating conditions. Subject to alterations and errors excepted. Applicable also to illustrations.  
Copyright © 2015 Wacker Neuson SE.