

“GP” Diesel Open Frame Generator



Control Panel
LED3 / LED4 / LED5 display optional
voltage, frequency, current,
power output, hours meter
ATS, remote control optional



AVR Regulation
ensures smooth voltage output
soft start for high current



32mm frame
strong & reliable & big fuel tank



Rubber absorber & bracket
reduce engine vibration evenly

DG7500LE-3

(Product might be different from photographs shown)

1

	GENERATOR MODEL	DG2500L/E	DG4000L/E	DG6000L/E	DG6000L/E-3	DG7500L/E	DG7500L/E-3
GENERATOR SET	Frequency (Hz)	50	50	50	50	50	50
	Rated Power (kVA)	1.8	2.8	4.5	5.5	5	6.25
	Max. Power (kVA)	2	3	5	6.25	5.5	6.9
	Voltage (V)	220	220	220	380/220	220	380/220
	Current (A)	9	15	25	8.1	27.5	9
	Sockets	2x16A	2x16A	2x16A	1x16A/1x32A	2x16A	1x16A/1x32A
	Display	LED3	LED3	LED3	LED3	LED3	LED3
	Fuel Tank Capacity (L)	14	14	14	14	14	14
	Running Time (hr.)	11	8	5.8	5.8	5.6	5.6
	Noise Level behind 7 Meters (dBA)	77	77	79	79	79	79
	DC Output (V/A)	12/8.3	12/8.3	12/8.3	12/8.3	12/8.3	12/8.3
Battery (Ah)	30	30	30	30	30	30	
ENGINE	Engine Type	Diesel	Diesel	Diesel	Diesel	Diesel	Diesel
	Engine	D200/E	D300/E	D400/E	D400/E	D500/E	D500/E
	Power Output (HP)	4.2	6	10	10	12	12
	Start Method	Manual / Electric	Manual / Electric	Manual / Electric	Manual / Electric	Manual / Electric	Manual / Electric
	Displacement (cc)	211	296	418	418	456	456
Old Capacity (L)	0.75	1.1	1.65	1.65	1.65	1.65	
LOG. DATA ALTERNATOR	Alternator	AL2	AL3	AL5	AL5-3	AL6	AL6-3
	Rated Power (kVA)	2	3	5	6.3	6	7.5
	Power Factor (Cos)	1	1	1	0.8	1	0.8
	Voltage Regulation	Brush / AVR	Brush / AVR	Brush / AVR	Brush / AVR	Brush / AVR	Brush / AVR
	N.W. (kg)	66	79	114	116	118	120
	G.W. (kg)	69	83	118	120	122	124
Products Size (mm)	610x460x530	680x460x560	720x480x600	720x480x600	720x480x600	720x480x600	

For further information, please feel free to contact Mr. Johnson Kwan on 92363957 on 2690 3509, thx!